

SPA-80M-1-1200 Solid State Power Amplifier

(80MHz - 1GHz, 1200W)

Key Features

- Multi-octave broadband performance
- High output power
- Wide dynamic range
- High-efficiency GaN technology
- Low power consumption
- Low spurious signal
- Forward/reverse power monitoring
- Extremely load-resistant
- Over voltage, over temperature, over current protection
- Optional overdrive protection
- CE, RoHS certification



Overview

Saluki SPA-80M-1-1200 is a solid-state RF power amplifier with an output frequency of 80MHz to 1GHz and an output power of 1200W. Its design is based on the most advanced LDMOS technology in the industry, and its power output is efficient and reliable. It is mainly used for testing and measuring instruments, Communication or interference, aviation control and other fields. The product has functions such as temperature and current detection, alarm protection and so on.

Technical Specifications

SPA-80M-1-1200			
Frequency Range	80MHz - 1GHz	Input Power	0dBm (max.)
Output Power	1200W (min.)	Harmonic	-15dBc (typ.)
P1dB Output Power	f<650MHz: >1000W F>650MHz: >850W	Background Noise	-40dBm/MHz (max.)
Gain	60dB (min.)	Spurious	-60dBc (max.)
Gain Flatness	± 3dB (max.)	Input VSWR	1.5:1 (typ.)

SPA-80M-1-1200 Solid State Power Amplifier

(80MHz - 1GHz, 1200W)

Adjustable Gain	20dB (max.)	Impedance	50 ohm
Input Port	Type-N (female)	Output Port	7/16
Communication Interface	LAN, GPIB	Power Supply	AC 220V Three-phase, 60A, 10 square wire
Dimension	19", 33U	Cooling Type	Air cooling
Operating Temperature	0 - 50°C	Display	LED screen

Note: Information will conduct the necessary updates, the contents of this document are subject to change without notice.